



ELECTRICAL

Breaker ID Circuit Breaker Finder



Finding the right circuit just became a simple, 1-person operation.

With the Breaker ID, you don't have to shut off power to the entire house, or go through trial-and-error, accidentally shutting off things you don't want to. A vital tool for both homeowners and contractors, the Breaker ID finds the right circuit breaker every time.

The Breaker ID has two parts: a transmitter that plugs into a circuit via a standard outlet, and sends a signal down the wire connecting that circuit, and a receiver wand which is used to scan the circuit breaker panel.

Simply plug the transmitter into an electrical outlet and then scan your circuit breaker panel twice to identify which breaker operates that outlet. During the first scan, the Breaker ID may indicate more than one breaker as it memorizes each circuit, but on the second scan, the Breaker ID will identify the correct circuit breaker with a green LED light and audio tone.



SPECIFICATIONS	
Dimensions	Receiver: 7 in. L x 1.9 in. H x 1.4 in. W (178 mm x 48 mm x 36 mm) Transmitter: 5" L x 2.1" H x 1.8" W (127 mm x 53 mm x 46 mm)
Weight	Receiver: 3.4 oz. (96 g) without battery Transmitter: 4.0 oz. (113 g)
Battery Type	9-V alkaline (not included)
Estimated Battery Life	Approximately 50 hours with 9 V alkaline battery
Power	Receiver: 9 V transistor type Transmitter: 110-120 V AC, 1.5 W max, folding 2-prong AC plug
Operating Temperature	41°F to 104° (5°C to 66°C)
Storage Temperature	-20°F to 150° (-29°C to 66°C)
Humidity	80% RH (non-condensing)
Water Resistance	Splash resistant, not waterproof
Compliance Certifications	UL, CUL, FCC

- Easy 1-person operation
- Scan for easy identification and labeling of all breakers
- Finds breakers faster and more efficiently with no accidental shutoffs
- Automatic calibration
- Lights and audio indicate circuit location
- Units snap together for storage



Scan for Electrical

©2011 Zircon Corporation • C/N 1867 07/11